

ScanSnap S1300i

Simple, Speedy & Compact.
From Paper to PDF in One Touch!



- ▶ Compact design with minimum footprint
- ▶ Fast scanning with portability
- ▶ Various functions for making your daily work easier and simpler
- ▶ Best experience with ScanSnap Home

General Specifications

| | | | |
|--------------------------------|--------------------------------|---|--|
| Product name | | ScanSnap S1300i | |
| Scanner type | | ADF (Automatic Document Feeder), duplex scanning | |
| Scanning modes | | Color, grayscale, monochrome, automatic (color / grayscale / monochrome detection) | |
| Image sensor | | CIS (Contact Image Sensor) x 2 | |
| Light source | | 3 Color LED (Red / Green / Blue) | |
| Optical resolution | | 600 dpi | |
| Scanning speed (A4 portrait)*1 | AC adapter | Auto mode*2 | Simplex / Duplex: 6 ppm |
| | | Normal mode | Color / Grayscale: 150 dpi, Monochrome: 300 dpi, Simplex / Duplex: 12 ppm |
| | | Better mode | Color / Grayscale: 200 dpi, Monochrome: 400 dpi, Simplex / Duplex: 9 ppm |
| | | Best mode | Color / Grayscale: 300 dpi, Monochrome: 600 dpi, Simplex / Duplex: 6 ppm |
| | | Excellent mode | Color / Grayscale: 600 dpi, Monochrome: 1,200 dpi, Simplex / Duplex: 1 ppm |
| | USB bus powered*3 | Auto mode*2 | Simplex / Duplex: 2 ppm |
| | | Normal mode | Color / Grayscale: 150 dpi, Monochrome: 300 dpi, Simplex / Duplex: 4 ppm |
| | | Better mode | Color / Grayscale: 200 dpi, Monochrome: 400 dpi, Simplex / Duplex: 3ppm |
| | | Best mode | Color / Grayscale: 300 dpi, Monochrome: 600 dpi, Simplex / Duplex: 2ppm |
| | | Excellent mode | Color / Grayscale: 600 dpi, Monochrome: 1,200 dpi, Simplex / Duplex: 1 ppm |
| Document size | Normal mode | A4, A5, A6, B5, B6, Business card, Post card, Letter, Legal and Custom sizes (Max: 216 x 360 mm (8.5 x 14.17 in.), Min: 50.8 x 50.8 mm (2 x 2 in.) / Automatically recognizes document size | |
| | Long paper scanning*4 | 863 mm (34 in.) | |
| Paper weight (Thickness) | | 64 to 104.7 g/m ² (17.1 to 28.0 lb) | |
| Paper chute capacity*5 | | Maximum 10 sheets (A4, 80 g/m ² or 20 lb) | |
| Interface | | USB 2.0 (USB 1.1 Compatible) | |
| Power requirement | AC adapter | AC 100 to 240 V, 50 / 60 Hz | |
| | USB bus power | 5 V / 1 A (0.5 A x 2 port) | |
| Power consumption | Power cable connection | During operation: 9 W or less, During sleep mode: 2.6 W or less, During off mode: 0.5 W or less | |
| | USB bus power cable connection | During operation: 5 W or less, During sleep mode: 2 W or less, During off mode: 0.5 W or less | |
| Operation environment | | Temperature: 5 to 35 °C (41 to 95 °F) Relative humidity: 20 to 80 % (Non-condensing) | |
| Dimensions (W x D x H)*6 | | 284 x 99 x 77 mm (11.18 x 3.90 x 3.03 in.) | |
| Device weight | | 1.4 kg (3.08 lb) | |
| Environmental compliance | | ENERGY STAR® / RoHS | |
| Multifeed detection | | Length check | |
| Driver | | Specific driver ● Windows®: Does not support TWAIN / ISIS™ ● macOS: Does not support TWAIN | |

*1 Scanning speeds may vary due to the system environment used. *2 Documents measuring approximately 148 mm in length or less are scanned in "Best mode", while other documents are scanned in "Better mode". *3 When using the USB bus power cable, the personal computer must have two USB ports: one for power feeding, the other for USB cable connection. *4 ScanSnap S1300i is capable of scanning documents that exceed A4 size in length. It supports the scanning of longer documents in all modes, except for "Excellent mode". *5 Maximum capacity varies, depending upon paper weight. *6 When chuter is closed.

Software

| | |
|--------------------------------|-------|
| Windows® | macOS |
| ScanSnap Home*1 | |
| ABBYY FineReader for ScanSnap™ | |

*1 ScanSnap Home installation requires a computer and Internet. Activation is also necessary for software use. Please visit the company website for download information. <https://scansnap.fujitsu.com/g-support/en>

Options

| Description | Part number | Remarks |
|---------------------------|--------------|---|
| ScanSnap S300 Soft Case*1 | PA03541-0004 | Intended for ScanSnap S1300i, S1300, S300, S300M and included items |

*1 This product has been especially designed for storing and carrying ScanSnap S1300i / S1300 / S300 / S300M. Please note that this product is not guaranteed to withstand damage by excessive shock or external pressure.

This scanner is designed to digitize materials that can be reproduced lawfully, in accordance with applicable copyright regulations and other laws. ScanSnap users are responsible for how they use this scanner. It is imperative that ScanSnap users comply with all applicable local rules and laws, including, without limitation, copyright laws when using this scanner.

*ABBYY and FineReader are trademarks of ABBYY Software, Ltd. which may be registered in some jurisdictions. ABBYY™ FineReader™ Engine ©ABBYY. OCR by ABBYY. *Evernote is a registered trademark or trademark of Evernote Corporation. *Google, Google Drive, Android and Google Play are registered trademarks or trademarks of Google Inc. *Intel, Pentium, and Intel Core are registered trademarks or trademarks of Intel Corporation in the United States and other countries. *ISIS™ is a registered trademark of EMC Corporation in the United States. *Mac, macOS, and the Mac logo are trademarks of Apple Inc. *ScanSnap, the ScanSnap logo and ScanSnap Home are registered trademarks or trademarks of PFI Limited in Japan. *Wi-Fi and Wi-Fi Protected Setup are trademarks of Wi-Fi Alliance. *Other company names and product names are the trademarks or registered trademarks of the respective companies.

ABBYY FineReader®



PFI Limited, a Fujitsu company, has determined that this product meets the ENERGY STAR® guidelines for energy efficiency. ENERGY STAR® is a registered trademark of the United States.

For more ScanSnap related information, visit our website at : fujitsu-scansnap.com

| | | |
|-----------------------------|---|---|
| ⚠ Safety Precautions | Be sure to carefully read all safety precautions prior to using this product and use this device as instructed. | Do not place this device in wet, moist, steamy, dusty or oily areas. Using this product under such conditions may result in electrical shock, fire or damage to this product. |
|-----------------------------|---|---|

Specifications are subject to change without notice.

©2019 PFI Limited Printed in some country 2017.12 U-100 SZX-50K7

shaping tomorrow with you

ScanSnap S1300i System Requirements

Windows®

| | | |
|-------------------------------|--------------------|---|
| Recommended operating systems | | Windows® 10 (32-bit / 64-bit) *1 Windows® 8.1 (32-bit / 64-bit) *1 Windows® 7 (32-bit / 64-bit) |
| Hardware requirements *2 | CPU *3 | Intel® Core™ i5 2.5 GHz or higher |
| | Memory capacity *3 | 4 GB or more |
| | Display resolution | 1,024 x 768 pixels or higher |
| | Disk capacity *4 | 3.8 GB or more of free hard disk space |

*1 Operate Windows in desktop mode. *2 The ScanSnap device may not work if the connected computer does not meet these requirements. *3 Scanning speeds may drop if the recommended CPU, memory capacity and USB 1.1 requirements are not met. *4 Microsoft .NET Framework 4.7 or later must be installed. If it is not installed, it is installed with ScanSnap Home. Up to 4.5 GB of disk space is required for the installation. *Please refer to the ScanSnap website for the latest support information of the driver and applications. Compatibility may differ depending on the software's version. *The system requirements may change depending on the duration of support and the support policy of the companies that make the software.

Mac

| | | |
|-------------------------------|--------------------|--|
| Recommended operating systems | | macOS v.10.12.4 or later |
| Hardware requirements *1 | CPU *2 | Intel® Core™ i5 2.5 GHz or higher |
| | Memory capacity *2 | 8 GB or more |
| | Display resolution | 1,024 x 768 pixels or higher |
| | Disk capacity | 2.0 GB or more of free hard disk space |

*1 The ScanSnap device may not work if the connected computer does not meet these requirements. *2 Scanning speeds may drop if the recommended CPU, memory capacity and USB 1.1 requirements are not met. *Please refer to the ScanSnap website for the latest support information of the driver and applications. Compatibility may differ depending on the software's version. *The system requirements may change depending on the duration of support and the support policy of the companies that make the software.

Included items

- AC cable
- USB bus power cable
- Safety Precautions
- AC adapter
- USB cable

Consumables

| Description | Part number | Remarks |
|---------------|--------------|---|
| Pick Roller*1 | PA03541-0001 | Life cycle: Every 100,000 sheets or one year. |
| Pad Assy*1 | PA03541-0002 | Life cycle: Every 10,000 sheets or one year. |
| Cleaner F1 | PA03950-0352 | 100 ml bottle : For use on the Pick Roller and Pad Assy |
| Cleaning Wipe | PA03950-0419 | 1 pack (24 packets) : For use on the Pick Roller and Pad Assy |

*1 These recommended lifetimes are for 80 g/m² (20 lb) A4 sized documents. Therefore, appropriate replacement lifetimes may vary for other document types.